





PUT LED CENTER 92706

202 914 929



[View on website](#)



General info

LOCATION	indoor
INSTALLATION	Ceiling Recessed
RECESSED DEPTH (MM)	145 + H (PUT..CENTER)
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.2
ADJUSTABILITY	non adjustable
INFORMATION	LENS SP-6° EXCL.LED POWER SUPPLY 700-1050mA-DC

Electrical info

CLASS	III
DIM TYPE	depending on power supply
ENERGY CLASS	F

Lightsource info

LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 2-3,2W / CRI>90 / 2700K / 201-280lm
SDCM	SDCM3
RISKGROUP	RG2 (threshold 0,6m)
LED TECHNICS (LIGHT SOURCE)	280lm // 3,2W // 88lm/W
LED TECHNICS (LUMINAIRE)	237lm // 4W // 64lm/W

Remarks

CENTER PLATE INCLUDED WITH HOLE IN ONE

Requirements










LED POWER SUPPLY 700 / 1050mA-DC DIM

For detailed installation instructions, please consult the manual: [202_914_XXX_HAND.pdf](#)

PUT LED CENTER 92706


202 914 929

FINISH YOUR SPECIFICATION

LED power supplies			#
	300 90 68	LED POWER SUPPLY MULTI-POWER DIM5	2->15(6) / - / - ☐
	300 90 69	LED POWER SUPPLY MULTI-POWER HV DIM9	28(18) / - / - ☐
	300 90 124	LED POWER SUPPLY MULTI-POWER DIM7	2->9(6) / - / - ☐
	300 90 125	LED POWER SUPPLY MULTI-POWER MINI DIM5	2->9(6) / - / - ☐
	300 90 136	LED POWER SUPPLY MULTI-POWER HC DIM9	- / 13(11) / - ☐
	300 90 148	LED POWER SUPPLY 1050mA-DC / 22W	6(3) ☐
	21012 005W	LED POWER SUPPLY MULTI-POWER COMPACT WDL	2->16 / 2 -> 11 / - ☐
	21012 0490	LED POWER SUPPLY 700mA-DC / 30W IP68	2->14(7) ☐
	21032 0315	LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W DIM5	2->13 ☐

PUT LED CENTER 92706

202 914 929




21032 0385 LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W PRO DIM5


2->13



Hole In One case for Put



202 91 97 01 HOLE IN ONE R15 LED



202 91 97 11 HOLE IN ONE S15 LED



Notes: