



ENTERO RD-S 92710 B

28401 9210 B



AVAILABLE IN

BLACK 28401 9210 B

FULL WHITE 28401 9210 FW

GOLD COLOURED 28401 9210 GC

WHITE 28401 9210 W



[View on website](#)

General info

LOCATION	indoor
INSTALLATION	Ceiling Recessed
CUTOUT SHAPE/SIZE (MM)	round - 76
RECESSED DEPTH (MM)	100
THICKNESS OF MOUNTING SURFACE (MM)	max.16
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.24
ADJUSTABILITY	0° to 30° swiveling, 355° rotatable
INFORMATION	LENS SP-10° EXCL.LED POWER SUPPLY 350-500mA-DC

Electrical info

CLASS	III
DIM TYPE	depending on power supply
ENERGY CLASS	F
CERTIFICATES	CB, ENEC, EPD

Lightsource info

LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 3,9-5,7W / CRI>90 (R9: 56) / 2700K / 385-519lm
TM-30 VALUES	rf: 91 / Rg: 99
SDCM	SDCM2
RISKGROUP	RG2 (threshold 0,6m)
LM80	L90B10 > 41000
LED TECHNICS (LIGHT SOURCE)	519lm // 5,7W // 90lm/W
LED TECHNICS (LUMINAIRE)	502lm // 7W // 77lm/W

Requirements

LED POWER SUPPLY 350 / 500mA-DC DIM

Options

ENTERO RD-S MOUNTING SET S2

ENTERO RD-S 92710 B

28401 9210 B

Accessories

ENTERO S HONEYCOMB

For detailed installation instructions, please consult the manual: [28401_XXX0_HAND.pdf](#)

CEILING COMPATIBILITY


Ceiling Type	Mounting Kit
 System ceiling	-
 Plasterboard	-
 Stucanet	-
 Wood	-
 Concrete	 ENTERO RD-S MOUNTING SET S2 Required
 Concrete + plaster	 ENTERO RD-S MOUNTING SET S2 Required
 Lintel + plaster	 ENTERO RD-S MOUNTING SET S2 Required
 Hollow-core slab	 ENTERO RD-S MOUNTING SET S2 Required
 Hollow-core slab + plaster	 ENTERO RD-S MOUNTING SET S2 Required
 Stretched ceiling	-

ENTERO RD-S 92710 B

28401 9210 B

FINISH YOUR SPECIFICATION

Emergency units



21032 0270 B EMERGENCY UNIT 7W / 1h + LED INDICATOR HOLDER B

☐








21032 0270 W EMERGENCY UNIT 7W / 1h + LED INDICATOR HOLDER W

☐

 DELTALIGHT®










ENTERO RD-S 92710 B

28401 9210 B

LED power supplies			#
	300 90 63 LED POWER SUPPLY MULTI-POWER DIM9	1->6(6) / 1->6(6)	☐
	300 90 68 LED POWER SUPPLY MULTI-POWER DIM5	1->4(3) / 1->4(2) / 1->3(2)	☐
	300 90 69 LED POWER SUPPLY MULTI-POWER HV DIM9	3->9(9) / 1->9(6)	☐
	300 90 124 LED POWER SUPPLY MULTI-POWER DIM7	2->4(3) / 1->3(2) / 1->3(2)	☐
	300 90 125 LED POWER SUPPLY MULTI-POWER MINI DIM5	2->4(3) / 1->3(2) / 1->3(2)	☐
	21012 0010 LED POWER SUPPLY MULTI POWER	2->3 / 2->3	☐
	21012 0021 LED POWER SUPPLY MULTI POWER DIM1	2->4 / 2->4	☐
	21012 0035 LED POWER SUPPLY MULTI POWER DIM5	2->4 / 2->4	☐
	21012 005W LED POWER SUPPLY MULTI-POWER COMPACT WDL	1->4 / 1->4 / 1->4	☐

ENTERO RD-S 92710 B


28401 9210 B

	21012 0258 LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8	2->2 ☐
	21012 0268 LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8	3->3 ☐
	21012 0278 LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8	2->2 ☐
	21012 0288 LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8	4->4 ☐
	21012 0298 LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8	1->3 / 1->3 / 1->3 ☐
	21012 0480 LED POWER SUPPLY 350mA-DC / 17W IP68	1->4(3) ☐
	21012 0500 LED POWER SUPPLY 500mA-DC / 24W IP68	1->4(2) ☐
	21032 0295 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5	1->3 ☐
	21032 0305 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5	1->3 ☐

ENTERO RD-S 92710 B

28401 9210 B


Light altering devices



28500 0050 B ENTERO S HONEYCOMB SINGLE USE B



Mounting set S2



28500 0190 ENTERO RD-S MOUNTING SET S2



Notes: