



ENTERO RD-M 92710 B

28409 9210 B



AVAILABLE IN

BLACK 28409 9210 B

FULL WHITE 28409 9210 FW

GOLD COLOURED 28409 9210 GC

WHITE 28409 9210 W



[View on website](#)



General info

LOCATION	indoor
INSTALLATION	Ceiling Recessed
CUTOUT SHAPE/SIZE (MM)	round - 92
RECESSED DEPTH (MM)	130
THICKNESS OF MOUNTING SURFACE (MM)	max.16
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.43
ADJUSTABILITY	0° to 30° swiveling, 355° rotatable
INFORMATION	LENS SP-10° EXCL.LED POWER SUPPLY 350-700mA-DC

Electrical info

CLASS	III
DIM TYPE	depending on power supply
ENERGY CLASS	F
CERTIFICATES	CB, ENEC, EPD

Lightsource info

LIGHTSOURCE NAME	LED
LIGHTSOURCE	LED array 3,9-8,2W / CRI>90 (R9: 56) / 2700K / 385-677lm
TM-30 VALUES	rf: 91 / Rg: 99
SDCM	SDCM2
RISKGROUPE	RG2 (threshold 0,6m)
LM80	L90B10 > 41000
LED TECHNICS (LIGHT SOURCE)	677lm // 8,2W // 83lm/W
LED TECHNICS (LUMINAIRE)	610lm // 9W // 65lm/W

Remarks

Max.500mA when using accessories

Requirements

LED POWER SUPPLY 350 / 500 / 700mA-DC DIM

 DELTALIGHT®

ENTERO RD-M 92710 B

28409 9210 B

Options

ENTERO RD-M MOUNTING SET S2


Accessories

ENTERO M HONEYCOMB

For detailed installation instructions, please consult the manual: [28409_XXX0_HAND.pdf](#)

CEILING COMPATIBILITY









Ceiling Type	Mounting Kit		
 System ceiling	-		
 Plasterboard	-		
 Stucanet	-		
 Wood	-		
 Concrete		ENTERO RD-M MOUNTING SET S2	Required
 Concrete + plaster		ENTERO RD-M MOUNTING SET S2	Required
 Lintel + plaster		ENTERO RD-M MOUNTING SET S2	Required
 Hollow-core slab		ENTERO RD-M MOUNTING SET S2	Required
 Hollow-core slab + plaster		ENTERO RD-M MOUNTING SET S2	Required
 Stretched ceiling	-		

☐

 DELTALIGHT®


ENTERO RD-M 92710 B

28409 9210 B

LED power supplies			#
	300 90 63 LED POWER SUPPLY MULTI-POWER DIM9	1->6(6) / 1->6(6) / 1->6(4)	☐
	300 90 68 LED POWER SUPPLY MULTI-POWER DIM5	1->4(3) / 1->4(2) / 1->3(2) / 1->3(1)	☐
	300 90 69 LED POWER SUPPLY MULTI-POWER HV DIM9	3->9(9) / 1->9(6) / 1->6(4)	☐
	300 90 124 LED POWER SUPPLY MULTI-POWER DIM7	2->4(3) / 1->3(2) / 1->3(2) / 1->2(1)	☐
	300 90 125 LED POWER SUPPLY MULTI-POWER MINI DIM5	2->4(3) / 1->3(2) / 1->3(2) / 1->2(1)	☐
	21012 0010 LED POWER SUPPLY MULTI POWER	2->3 / 2->3 / 1->3	☐
	21012 0021 LED POWER SUPPLY MULTI POWER DIM1	2->4 / 2->4 / 1->4	☐
	21012 0035 LED POWER SUPPLY MULTI POWER DIM5	2->4 / 2->4 / 1->4	☐
	21012 005W LED POWER SUPPLY MULTI-POWER COMPACT WDL	1->4 / 1->4 / 1->4 / 1->4	☐


ENTERO RD-M 92710 B

28409 9210 B




21012 0258 LED POWER SUPPLY MULTI POWER 200-350 / 10W DIM8

2->2 ☐




21012 0268 LED POWER SUPPLY MULTI POWER 200-350 / 15W DIM8

3->3 ☐




21012 0278 LED POWER SUPPLY MULTI POWER 500-700 / 20W DIM8

2->2 / 2->2 ☐




21012 0288 LED POWER SUPPLY MULTI POWER 500-700 / 36W DIM8

4->4 / 3->4 ☐




21012 0298 LED POWER SUPPLY MULTI POWER 250-900 / 20W DIM8

1->3 / 1->3 / 1->3 / 1->2 ☐




21012 0480 LED POWER SUPPLY 350mA-DC / 17W IP68

1->4(3) ☐




21012 0490 LED POWER SUPPLY 700mA-DC / 30W IP68

1->3(1) ☐




21012 0500 LED POWER SUPPLY 500mA-DC / 24W IP68

1->4(2) ☐



21032 0295 LED POWER CONVERTER 48V-DC to 350 mA-DC / 15W DIM5

1->3 ☐




21032 0305 LED POWER CONVERTER 48V-DC to 500 mA-DC / 22W DIM5

1->3 ☐

ENTERO RD-M 92710 B

28409 9210 B




21032 0315 LED POWER CONVERTER 48V-DC to 700 mA-DC / 25W DIM5

1->3



Light altering devices



28500 0110 B ENTERO M HONEYCOMB SINGLE USE B



Mounting set S2



28500 0200 ENTERO RD-M MOUNTING SET S2



Notes: