





## M26L - SPY 52 WALLWASH SOFT 930 MDL B

19892 9000 B

AVAILABLE IN  
**BLACK** 19892 9000 B  
**FLEMISH BRONZE** 19892 9000 FBR  
**FLEMISH GOLD** 19892 9000 FG  
**GOLD COLOURED** 19892 9000 GC  
**WHITE** 19892 9000 W



 [View on website](#)

General info	
<b>LOCATION</b>	indoor
<b>INSTALLATION</b>	Low voltage systems Low voltage system mounted
<b>INGRESS PROTECTION</b>	IP20
<b>WEIGHT (KG)</b>	0.3
<b>ADJUSTABILITY</b>	0° to 90° swiveling, 360° rotatable
<b>INFORMATION</b>	WALLWASH LENS EXCL.LED POWER SUPPLY 48V-DC

Electrical info	
<b>ELECTRICAL</b>	48V-DC
<b>CLASS</b>	III
<b>DIM TYPE</b>	MDL = 1-10V or DALI or push button
<b>ENERGY CLASS</b>	F
<b>CERTIFICATES</b>	ENEC, LCA

Lightsource info	
<b>LIGHTSOURCE NAME</b>	LED
<b>LIGHTSOURCE</b>	LED array 10,2W / CRI>90 (R9: 50) / 3000K-1800K / 1038lm
<b>SDCM</b>	SDCM2
<b>RISKGROUP</b>	RG1
<b>LM80</b>	L90B10 > 50000
<b>LED TECHNICS (LIGHT SOURCE)</b>	1038lm // 10,2W // 109lm/W
<b>LED TECHNICS (LUMINAIRE)</b>	490lm // 12W // 42lm/W

**Remarks**  
 Take a look at our **MAGNETIC PROFILES** movie

**Requirements**  
 LED POWER SUPPLY 48V-DC



## **M26L - SPY 52 WALLWASH SOFT 930 MDL B**

19892 9000 B

### **Options**

---

DIMMABLE MODULATOR

For detailed installation instructions, please consult the manual: [19892\\_XXX0\\_HAND.pdf](#)

**M26L - SPY 52 WALLWASH SOFT 930 MDL B**

19892 9000 B

**FINISH YOUR SPECIFICATION**

**Current supply**

#



**21032 0030** SMART 48 MODULATOR PLUG-IN WD

16

**SMART 48**

#



**300 90 011** SMART 48 MODULATOR DIM9

16



**300 90 012** SMART 48 MODULATOR WD

16


**LED power supplies**

#




**300 89 48 100** LED POWER SUPPLY 48V-DC / 100W DIN

8




**300 89 48 240** LED POWER SUPPLY 48V-DC / 240W DIN

20



**21012 0230** LED POWER SUPPLY 48V-DC / 100W

8



**21012 0240** LED POWER SUPPLY 48V-DC / 200W

17


# M26L - SPY 52 WALLWASH SOFT 930 MDL B

19892 9000 B


## COMPATIBLE COMPOSABLES

### SHIFTLINE M26L profile (+ SHIFTLINE M26L MATRIX)


### Available Colours




**23358 0000** SLM26L - PROFILE



**23358 0010** SLM26L - PROFILE 1m



**23358 0020** SLM26L - PROFILE 2m



**23358 0030** SLM26L - PROFILE 3m



Notes: