





## SUPERLOOP HC SBL OVAL M 927 B

### 20571 9200 B

AVAILABLE IN  
**BLACK** 20571 9200 B  
**FLEMISH BRONZE** 20571 9200 FBR  
**FLEMISH GOLD** 20571 9200 FG  
**WHITE** 20571 9200 W



[View on website](#)



#### General info

|                           |                                                                                                                                                                      |
|---------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>LOCATION</b>           | indoor                                                                                                                                                               |
| <b>INSTALLATION</b>       | Ceiling Suspended                                                                                                                                                    |
| <b>INGRESS PROTECTION</b> | IP20                                                                                                                                                                 |
| <b>WEIGHT (KG)</b>        | 4.5                                                                                                                                                                  |
| <b>ADJUSTABILITY</b>      | non adjustable                                                                                                                                                       |
| <b>INFORMATION</b>        | INCL.PC SBL<br>EXCL.LED POWER SUPPLY 900-1200mA-DC<br><p>INCL.4 x CABLE SUSPENSION SINGLE AUTO. 3.0m&nbsp;&nbsp;&nbsp;</p><br>INCL.1 x CABLE 2 x 0.75mm <sup>2</sup> |

#### Electrical info

|                     |                           |
|---------------------|---------------------------|
| <b>CLASS</b>        | III                       |
| <b>DIM TYPE</b>     | depending on power supply |
| <b>ENERGY CLASS</b> | E                         |
| <b>CERTIFICATES</b> | CB, ENEC, LCA             |

#### Lightsource info

|                                    |                                                                |
|------------------------------------|----------------------------------------------------------------|
| <b>LIGHTSOURCE NAME</b>            | LED                                                            |
| <b>LIGHTSOURCE</b>                 | LED cluster 36,3-49,5W / CRI>90 (R9: 59) / 2700K / 5217-6845lm |
| <b>SDCM</b>                        | SDCM3                                                          |
| <b>LM80</b>                        | L70 > 20000                                                    |
| <b>LED TECHNICS (LIGHT SOURCE)</b> | 6845lm // 49,5W // 138lm/W                                     |
| <b>LED TECHNICS (LUMINAIRE)</b>    | 4113lm // 57W // 72lm/W                                        |

#### Requirements

LED POWER SUPPLY 900 / 1200mA-DC DIM  
 SUPERLOOP POWERBOX H 900mA  
 SUPERLOOP POWERBOX H 1200mA

#### Options

CABLE BASE R / S  
 COVERSET R 62-90-100 / S 62-80-90  
 CONNECTION ST / CONNECTION TRIMLESS  
 SUSPENSION ST / SUSPENSION TRIMLESS





## **SUPERLOOP HC SBL OVAL M 927 B**

20571 9200 B

For detailed installation instructions, please consult the manual: [\*\*20571\\_XXX0\\_HAND.pdf\*\*](#)




FINISH YOUR SPECIFICATION




Current supply

|                                                                                  |                                                                       |                          |
|----------------------------------------------------------------------------------|-----------------------------------------------------------------------|--------------------------|
|  | <div><div><b>203 99 55 ANO</b></div><div>CABLE BASE R ANO</div></div> | <input type="checkbox"/> |
|                                                                                  | <div><div><b>203 99 55 B</b></div><div>CABLE BASE R B</div></div>     | <input type="checkbox"/> |
|                                                                                  | <div><div><b>203 99 55 W</b></div><div>CABLE BASE R W</div></div>     | <input type="checkbox"/> |
|  | <div><div><b>203 99 56 ANO</b></div><div>CABLE BASE S ANO</div></div> | <input type="checkbox"/> |
|                                                                                  | <div><div><b>203 99 56 B</b></div><div>CABLE BASE S B</div></div>     | <input type="checkbox"/> |
|                                                                                  | <div><div><b>203 99 56 W</b></div><div>CABLE BASE S W</div></div>     | <input type="checkbox"/> |

SUPERLOOP HC SBL OVAL M 927 B

20571 9200 B


| Power box                                                                         |                                                             | #                          |
|-----------------------------------------------------------------------------------|-------------------------------------------------------------|----------------------------|
|   | <b>321 55 312 ED1 B</b> SUPERLOOP POWERBOX H8 1200mA DIM1 B | 1 <input type="checkbox"/> |
|                                                                                   | <b>321 55 312 ED1 W</b> SUPERLOOP POWERBOX H8 1200mA DIM1 W | 1 <input type="checkbox"/> |
|   | <b>20548 0015 B</b> SUPERLOOP POWERBOX H9 900mA DIM5 B      | 1 <input type="checkbox"/> |
|                                                                                   | <b>20548 0015 W</b> SUPERLOOP POWERBOX H9 900mA DIM5 W      | 1 <input type="checkbox"/> |
|  | <b>20548 0025 B</b> SUPERLOOP POWERBOX H9 1200mA DIM5 B     | 1 <input type="checkbox"/> |
|                                                                                   | <b>20548 0025 W</b> SUPERLOOP POWERBOX H9 1200mA DIM5 W     | 1 <input type="checkbox"/> |

| LED power supplies                                                                 |                                                         | #                          |
|------------------------------------------------------------------------------------|---------------------------------------------------------|----------------------------|
|  | <b>300 90 129</b> LED POWER SUPPLY 900mA-DC / 60W DIM5  | 1 <input type="checkbox"/> |
|  | <b>300 90 130</b> LED POWER SUPPLY 1200mA-DC / 60W DIM5 | 1 <input type="checkbox"/> |
|  | <b>300 90 132</b> LED POWER SUPPLY 1200mA-DC / 70W DIM1 | 1 <input type="checkbox"/> |

**SUPERLOOP HC SBL OVAL M 927 B**

20571 9200 B

**Coversets**




**204 00 100 B** COVERSET R 100 B

☐


**204 00 100 W** COVERSET R 100 W

☐

**Suspension parts**



**328 10 01** SUSPENSION TRIMLESS O.F.A.

☐


**15225 0340 B** SUSPENSION ST B

☐

**15225 0340 W** SUSPENSION ST W

☐

**Electric connection parts**



**328 10 03** CONNECTION TRIMLESS O.F.A.

☐

**15225 0360 B** CONNECTION ST B

☐

**15225 0360 W** CONNECTION ST W

☐



**SUPERLOOP HC SBL OVAL M 927 B**

20571 9200 B

Notes: