





## M26L - SPY 391 SOFT 93020 MDL B

### 23437 9020 B

AVAILABLE IN  
**BLACK** 23437 9020 B  
**BRUSHED ALU** 23437 9020 BRA  
**BRUSHED ANTHRACITE** 23437 9020 BRAT  
**BRUSHED COPPER** 23437 9020 BRCU  
**BRUSHED GOLD** 23437 9020 BRG  
**BRUSHED OLD BRONZE** 23437 9020 BROB  
**FLEMISH BRONZE** 23437 9020 FBR  
**FLEMISH GOLD** 23437 9020 FG  
**GOLD COLOURED** 23437 9020 GC  
**PIANO BLACK** 23437 9020 PB  
**WHITE** 23437 9020 W



 [View on website](#)

General info	
<b>LOCATION</b>	indoor
<b>INSTALLATION</b>	Low voltage systems Low voltage system mounted
<b>INGRESS PROTECTION</b>	IP20
<b>WEIGHT (KG)</b>	0.3
<b>ADJUSTABILITY</b>	0° to 85° swiveling, 360° rotatable
<b>INFORMATION</b>	REFLECTOR FL-20° EXCL.LED POWER SUPPLY 48V-DC

Electrical info	
<b>ELECTRICAL</b>	48V-DC
<b>CLASS</b>	III
<b>DIM TYPE</b>	MDL = 1-10V or DALI or push button
<b>ENERGY CLASS</b>	F

Lightsource info	
<b>LIGHTSOURCE NAME</b>	LED
<b>LIGHTSOURCE</b>	LED array 6W / CRI>90 (R9: 50) / 3000K-1800K / 623lm
<b>TM-30 VALUES</b>	rf: 90 / Rg: 99
<b>SDCM</b>	SDCM2
<b>RISKGROUP</b>	RG1
<b>LM80</b>	L90B10 > 50000
<b>LED TECHNICS (LIGHT SOURCE)</b>	623lm // 6W // 105lm/W
<b>LED TECHNICS (LUMINAIRE)</b>	508lm // 7W // 74lm/W

Requirements	
SPY 39 TUBE	
LED POWER SUPPLY 48V-DC	



## **M26L - SPY 391 SOFT 93020 MDL B**

23437 9020 B

### **Options**

---

DIMMABLE MODULATOR

For detailed installation instructions, please consult the manual: [23437\\_XXX0\\_HAND.pdf](#)

**M26L - SPY 391 SOFT 93020 MDL B**

23437 9020 B

**FINISH YOUR SPECIFICATION**

**Current supply**

#



**21032 0030** SMART 48 MODULATOR PLUG-IN WD

16


**SMART 48**

#



**300 90 011** SMART 48 MODULATOR DIM9

16



**300 90 012** SMART 48 MODULATOR WD

16

**LED power supplies**

#



**300 89 48 100** LED POWER SUPPLY 48V-DC / 100W DIN

8



**300 89 48 240** LED POWER SUPPLY 48V-DC / 240W DIN

20



**21012 0230** LED POWER SUPPLY 48V-DC / 100W

8




**21012 0240** LED POWER SUPPLY 48V-DC / 200W

17

**M26L - SPY 391 SOFT 93020 MDL B**

23437 9020 B

**Finish your product**



**24144 0010 B** SPY 39 TUBE B

**24144 0010 FBR** SPY 39 TUBE FBR

**24144 0010 FG** SPY 39 TUBE FG

**24144 0010 GC** SPY 39 TUBE GC

**24144 0010 W** SPY 39 TUBE W




**24144 0070** SPY 39 TUBE SBL


**COMPATIBLE COMPOSABLES**

**SHIFTLINE M26L profile (+ SHIFTLINE M26L MATRIX)**


**Available Colours**




**23358 0000** SLM26L - PROFILE



**23358 0010** SLM26L - PROFILE 1m



**23358 0020** SLM26L - PROFILE 2m



**23358 0030** SLM26L - PROFILE 3m





**M26L - SPY 391 SOFT 93020 MDL B**

23437 9020 B

Notes: