





Image may differ from the actual product
Consult drawing for correct size and structure

INFORM 40 SQ 360 PDS DOWN
93063 DIM5 B-B
30720 9335 B-B

AVAILABLE IN
BLACK-BLACK 30720 9335 B-B
WHITE-BLACK 30720 9335 W-B



 [View on website](#)

General info	
LOCATION	indoor
INSTALLATION	Ceiling Surface mounted,Ceiling Suspended
INGRESS PROTECTION	IP20
WEIGHT (KG)	5.7
ADJUSTABILITY	non adjustable
INFORMATION	INCL.PRESENCE & DAYLIGHT SENSOR INCL.DIMMABLE LED POWER SUPPLY (DALI DT6) Power selection to be set on driver EXCL.CABLE SUSPENSION

Electrical info	
ELECTRICAL	220-240V / 0 50-60Hz
CLASS	I
POWER SUPPLY	YES
DIM TYPE	DALI
ENERGY CLASS	E

Lightsource info	
LIGHTSOURCE NAME	LED
LIGHTSOURCE	HO: LED cluster 48,4W / CRI>90 (R9: 50) / 3000K / 6989lm Or LED cluster 32,6W / CRI>90 (R9: 50) / 3000K / 5069lm
TM-30 VALUES	Rf: 92 / Rg: 100 rf: 92 / Rg: 100
SDCM	SDCM3
RISKGROUP	RG2
LM80	L80 > 60000
LED TECHNICS (LIGHT SOURCE)	HO: 6989lm // 48,4W // 145lm/W Or 5069lm // 32,6W // 155lm/W
LED TECHNICS (LUMINAIRE)	HO: 4836lm // 56W // 87lm/W Or 3507lm // 37W // 94lm/W

Options

INF40 SQ 320/360 - SUSPENSION SET
CABLE BASE R / S



INFORM 40 SQ 360 PDS DOWN 93063 DIM5 B-B

30720 9335 B-B


For detailed installation instructions, please consult the manual: [30720_XXX5_HAND.pdf](#)

INFORM 40 SQ 360 PDS DOWN 93063 DIM5 B-B

30720 9335 B-B

FINISH YOUR SPECIFICATION

Current supply



41 **203 99 55 ANO** CABLE BASE R ANO

☐

203 99 55 B CABLE BASE R B

☐

203 99 55 W CABLE BASE R W

☐


41 **203 99 56 ANO** CABLE BASE S ANO

☐

203 99 56 B CABLE BASE S B

☐

203 99 56 W CABLE BASE S W

☐

Fixation components



30710 0020 B INF40 SQ 320/360 - SUSPENSION SET 1,6m B

☐

30710 0020 W INF40 SQ 320/360 - SUSPENSION SET 1,6m W

☐


30710 0040 B INF40 SQ 320/360 - SUSPENSION SET 3,0m B


☐

30710 0040 W INF40 SQ 320/360 - SUSPENSION SET 3,0m W


☐

INFORM 40 SQ 360 PDS DOWN 93063 DIM5 B-B
30720 9335 B-B

Other



26510 0010 PDS REMOTE CONTROL

☐

26510 0020 PDS SENSOR PROGRAMMER

☐

Notes: