



# SOLI - FORM 110 DOWN-UP 92767 MDL B-B

27138 9220 B-B

AVAILABLE IN  
**BLACK-BLACK** 27138 9220 B-B  
**BLACK-FLEMISH GOLD** 27138 9220 B-FG  
**WHITE-BLACK** 27138 9220 W-B  
**WHITE-WHITE** 27138 9220 W-W



 [View on website](#)

General info	
LOCATION	indoor
INSTALLATION	Low voltage systems Low voltage system mounted
INGRESS PROTECTION	IP20
WEIGHT (KG)	0.9
ADJUSTABILITY	non adjustable
INFORMATION	INCL.48 x REFLECTOR FL-67° EXCL.LED POWER SUPPLY 48V-DC

Electrical info	
ELECTRICAL	48V-DC
CLASS	III
DIM TYPE	MDL = 1-10V or DALI or push button
ENERGY CLASS	E
CERTIFICATES	CB, ENEC

Lightsource info	
LIGHTSOURCE NAME	LED
LIGHTSOURCE	DOWN: LED cluster 14,1W / CRI>90 (R9: 50) / 2700K / 2026lm UP: LED cluster 14,1W / CRI>90 (R9: 50) / 2700K / 2026lm
TM-30 VALUES	Rf: 93 / Rg: 100
SDCM	SDCM3
RISKGROUP	RG2
LM80	L80 > 60000
LED TECHNICS (LIGHT SOURCE)	DOWN: 2026lm // 14,1W // 144lm/W UP: 2026lm // 14,1W // 144lm/W
LED TECHNICS (LUMINAIRE)	DOWN: 1722lm // 16W // 106lm/W UP: 1357lm // 16W // 84lm/W

Requirements
LED POWER SUPPLY 48V-DC

Options
DIMMABLE MODULATOR

**SOLI - FORM 110 DOWN-UP 92767 MDL B-B**


27138 9220 B-B

For detailed installation instructions, please consult the manual: [27138\\_XXX0\\_HAND.pdf](#)

**FINISH YOUR SPECIFICATION**


**SMART 48**

#



**300 90 011** SMART 48 MODULATOR DIM9

5




**300 90 012** SMART 48 MODULATOR WD

5


**LED power supplies**

#




**300 89 48 100** LED POWER SUPPLY 48V-DC / 100W DIN

3




**300 89 48 240** LED POWER SUPPLY 48V-DC / 240W DIN

7



**21012 0230** LED POWER SUPPLY 48V-DC / 100W

3



**21012 0240** LED POWER SUPPLY 48V-DC / 200W

6


**SOLI - FORM 110 DOWN-UP 92767 MDL B-B**

27138 9220 B-B


**COMPATIBLE COMPOSABLES**

**SOLISCAPE profile**

**Available Colours**



**27111 0020** SOLI - PROFILE 2m



**27111 0030** SOLI - PROFILE 3m



Notes:

Empty rectangular box for notes.